

Kaabli suuruse ja pikkuse määramine.

Õige kaabel

Häireteta toimimise seisukohast on oluline kasutada piisavalt tugevat kaablit. Vali õige kaabli suurus ja pikkus allpool toodud tabelis.

Mootor kW	3 x 400 V, DOL					
	1,5 mm ²	2,5 mm ²	4,0 mm ²	6,0 mm ⁶	10,0 mm ²	16,0 mm ²
0,37	768					
0,55	489	811				
0,75	416	691				
1,1	281	467	744			
1,5	219	363	579	862		
2,2	153	254	405	605	997	
3,0	113	188	300	447	736	
4,0	89	147	235	350	578	909
5,5		106	169	251	414	651
7,5			126	187	309	485
9,3			103	154	254	400
11,0				133	219	345
15,0					161	254
18,5					132	208
22,0					112	176
30,0						129

Max. kaabli pikkus 1-faas, 230V.

Mootor		kaabli mm ²	
kW	hj	1.5	2.5
0.37	0.5	160	260
0.55	0.7	120	200
0.75	1.0	95	150

NORDEST GRUPP

Nordest Grupp OÜ
Humala 8, 10617 Tallinn
Tel: 51 36 876
www.puhasvesi.eu